



RF Solution offer a wide selection of Waveguide Circulator for global customers. BH3838-WR62 is a Waveguide Circulator in Frequency Range of 12.0~18.0 GHz. It is made of high quality materials under a high standard, the Bandwidth Max of this product is 10/100%, Insertion Loss Max is 0.30~0.40 dB and Isolation Min is 20.0~23.0 dB. The component has a good working performance and stability, it is ideal for handling a Forward Power of /.

Product Details

| | |
|-------------|---------------------------------------|
| Part Number | BH3838-WR62 |
| Description | 12.0 to 18.0 GHz Waveguide Circulator |

General Parameters

| | |
|-----------------------|----------------------------|
| Frequency Range | 12.0~18.0 GHz |
| Bandwidth Max | 10/100% |
| Insertion Loss Max | 0.30~0.40 dB |
| Isolation Min | 20.0~23.0 dB |
| Forward Power | / |
| VSWR Max | 1.15~1.25 |
| Impedance | 50 Ω |
| Connector Type | WR62 |
| Size | 38*38*33 mm |
| Weight | / |
| Operating Temperature | -40~+80 $^{\circ}\text{C}$ |
| Storage Temperature | / |
| ROHS Compliant | Yes |

Outline Drawing (mm)

