



RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-1805M1880A-S is a Band Stop Filter in Rejection Band of 1805~1880 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~1785MHz / 1900~6000MHz, Insertion Loss Max is 2.0 dB and Rejection Min is 60 dB. The component has a good working performance and stability, it is ideal for handling a Rated Power of 30 W.

Product Details

Part Number	BSF-1805M1880A-S
Description	1805~1880 MHz Band Stop Filter

General Parameters

Rejection Band	1805~1880 MHz
Pass Band	DC~1785MHz / 1900~6000MHz
Insertion Loss Max	2.0 dB
Rejection Min	60 dB
Rated Power	30 W
VSWR Max	2.00
Impedance	50 Ω
Connector Type	SMA-F
Size	157*40*22 mm
Surface Finishing	Black Painting
Operating Temperature	Ordinary temperature
Storage Temperature	-55~+85 $^{\circ}\text{C}$
ROHS Compliant	Yes

Outline Drawing (mm)

