

RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-1930M1990A-S is a Band Stop Filter in Rejection Band of 1930~1990 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~1915MHz / 2005~5000MHz, Insertion Loss Max is 2.0 dB and Rejection Min is 40 dB. The component has a good working performance and stability, it is ideal for handling a Rated Power of 20 W.

Product Details

Part Number	BSF-1930M1990A-S
Description	1930~1990 MHz Band Stop Filter


General Parameters

Rejection Band	1930~1990 MHz
Pass Band	DC~1915MHz / 2005~5000MHz
Insertion Loss Max	2.0 dB
Rejection Min	40 dB
Rated Power	20 W
VSWR Max	2.00
Impedance	50 Ω
Connector Type	SMA-F
Size	157*40*22 mm
Surface Finishing	Black Painting
Operating Temperature	Ordinary temperature
Storage Temperature	-55~+85 °C
ROHS Compliant	Yes

Outline Drawing (mm)



1930~1990 MHz Band Stop Filter





F R