



RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-3400M3600A-S is a Band Stop Filter in Rejection Band of 3400~3600 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~3370MHz / 3630~8000MHz, Insertion Loss Max is 2.0 dB and Rejection Min is 45 dB. The component has a good working performance and stability, it is ideal for handling a Rated Power of 10 W.

Product Details

Part Number	BSF-3400M3600A-S
Description	3400~3600 MHz Band Stop Filter

General Parameters

Rejection Band	3400~3600 MHz
Pass Band	DC~3370MHz / 3630~8000MHz
Insertion Loss Max	2.0 dB
Rejection Min	45 dB
Rated Power	10 W
VSWR Max	2.00
Impedance	50 Ω
Connector Type	SMA-F
Size	145*32*22 mm
Surface Finishing	Black Painting
Operating Temperature	Ordinary temperature
Storage Temperature	-55~+85 °C
ROHS Compliant	Yes

Outline Drawing (mm)

