



RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-400M600A-S is a Band Stop Filter in Rejection Band of 400~600 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~390MHz / 480~1500MHz, Insertion Loss Max is 2.0 dB and Rejection Min is 60dB@DC-800MHz. The component has a good working performance and stability, it is ideal for handling a Rated Power of 100 W.

Product Details

Part Number	BSF-400M600A-S
Description	400~600 MHz Band Stop Filter

General Parameters

Rejection Band	400~600 MHz
Pass Band	DC~390MHz / 480~1500MHz
Insertion Loss Max	2.0 dB
Rejection Min	60dB@DC-800MHz
Rated Power	100 W
VSWR Max	2.00
Impedance	50 Ω
Connector Type	SMA-F
Size	210*160*55 mm
Surface Finishing	Black Painting
Operating Temperature	Ordinary temperature
Storage Temperature	-55~+85 °C
ROHS Compliant	Yes

Outline Drawing (mm)

