

RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-758M803A-S is a Band Stop Filter in Rejection Band of 758~803 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~743MHz / 818~1800MHz, Insertion Loss Max is 2.0 dB and Rejection Min is 40 dB. The component has a good working performance and stability, it is ideal for handling a Rated Power of 10 W.

## **Product Details**

Part Number	BSF-758M803A-S
Description	758~803 MHz Band Stop Filter

## **General Parameters**

Rejection Band	758~803 MHz
Pass Band	DC~743MHz / 818~1800MHz
Insertion Loss Max	2.0 dB
Rejection Min	40 dB
Rated Power	10 W
VSWR Max	2.00
Impedance	50 Ω
Connector Type	SMA-F
Size	121*52*24 mm
Surface Finishing	Black Painting
Operating Temperature	Ordinary temperature
Storage Temperature	-55~+85 °C
ROHS Compliant	Yes

## Outline Drawing (mm)

F

R

24





