

RF Solution offer a wide selection of Band Stop Filter for global customers. BSF-880M915A-S is a Band Stop Filter in Rejection Band of 880~915 MHz. It is made of high quality materials under a high standard, the Pass Band of this product is DC~860MHz / 935~2000MHz, Insertion Loss Max is 1.5 dB and Rejection Min is 40 dB. The component has a good working performance and stability, it is ideal for handling a Rated Power of 20 W.

## Product Details

| Part Number | BSF-880M915A-S               |
|-------------|------------------------------|
| Description | 869~894 MHz Band Stop Filter |

## **General Parameters**

| Rejection Band        | 880~915 MHz             |
|-----------------------|-------------------------|
| Pass Band             | DC~860MHz / 935~2000MHz |
| Insertion Loss Max    | 1.5 dB                  |
| Rejection Min         | 40 dB                   |
| Rated Power           | 20 W                    |
| VSWR Max              | 2.00                    |
| Impedance             | 50 Ω                    |
| Connector Type        | SMA-F                   |
| Size                  | 121*52*24 mm            |
| Surface Finishing     | Black Painting          |
| Operating Temperature | Ordinary temperature    |
| Storage Temperature   | -55~+85 °C              |
| ROHS Compliant        | Yes                     |

## Outline Drawing (mm)

869~894 MHz Band Stop Filter

121



24

25